




30x10 mm-es áramsínre, vagy max. 30mm átmérőjű kábelre húzható áramváltó.

Primer áram	Class				Szekunder áram (A)		Súly
	0,2s/ 0,5s	0,5	1	3	5A	1A	
A	VA	VA	VA	VA	5A	1A	kg
75			1,5	3	TARM3 75A	TARM3 1 75A	0,30
80			2,0	3	TARM3 80A	TARM3 1 80A	0,30
100	2,5	2,0	2,5	3	TARM3 100A	TARM3 1 100A	0,30
120	2,5	1,5	2,5	3	TARM3 120A	TARM3 1 120A	0,35
125	2,5	1,5	2,5	3	TARM3 125A	TARM3 1 125A	0,35
150	2,5	2,5	3,5	5	TARM3 150A	TARM3 1 150A	0,35
200	2,5	3,5	5,0	7	TARM3 200A	TARM3 1 200A	0,35
250	2,5	5,0	7,0	10	TARM3 250A	TARM3 1 250A	0,40
300	2,5	5,0	7,0	10	TARM3 300A	TARM3 1 300A	0,40
400	3,75	7,5	10,0	12	TARM3 400A	TARM3 1 400A	0,42



40x10 mm-es áramsínre, vagy max. 30mm átmérőjű kábelre húzható áramváltó.

Primer áram	Class				Szekunder áram (A)		Súly
	0,2s/ 0,5s	0,5	1,0	3,0	5A	1A	
A	VA	VA	VA	VA	5A	1A	kg
100			1,0	2,5	TARM4 100A	TARM4 1 100A	0,30
120	1		1,5	3,0	TARM4 120A	TARM4 1 120A	0,35
125	1		1,5	3,0	TARM4 125A	TARM4 1 125A	0,35
150	2		2,5	3,5	TARM4 150A	TARM4 1 150A	0,35
200	2,5	1,5	3,75	5	TARM4 200A	TARM4 1 200A	0,35
250	2,5	2,5	5	7	TARM4 250A	TARM4 1 250A	0,40
300	2,5	5,0	6	7	TARM4 300A	TARM4 1 300A	0,40
400	2,5	5,0	6	10	TARM4 400A	TARM4 1 400A	0,42
500	3,75	5,0	7,5	10	TARM4 500A	TARM4 1 500A	0,42
600	5,0	7,5	10	12	TARM4 600A	TARM4 1 600A	0,42
800	5,0	7,5	10	12	TARM4 800A	TARM4 1 800A	0,42

